

APPLICATION FOR UNITED STATES PATENT

FOR

INTERFACE BASED DESIGN USING A TABULAR PARADIGM

Inventors: Mark W. P. Dane
Avtar Singh Bahra
Stephen L. Bold
Shahram Najm
Nitin Surti

Prepared by: Columbia IP Law Group, PC
4900 SW Meadows Road, Suite 109
Lake Oswego, OR 97035
(503) 534-2800

Express Mail Label No. EL743035730US
Date of Deposit: June 11, 2001

09379928-061101

INTERFACE BASED DESIGN USING A TABULAR PARADIGM

This utility application claims priority to provisional application 60/240,547 file on October 13, 2000. This provisional application is incorporated herein by reference.

FIELD OF THE INVENTION

The present invention is related to the field of Electronic Design Automation. More specifically, this invention relates to the entry of electronic design descriptions in an electronic design system.

BACKGROUND OF THE INVENTION

Leading edge integrated circuit designs are becoming increasingly vast in terms of both size and complexity. Problems brought about by this increase in complexity are exacerbated by the need to bring products to market more rapidly to meet competitive pressures. The custom user design space is no exception to this phenomenon and both Application Specific Integrated Circuits (ASICs) and Field Programmable Gate Arrays (FPGAs) designs have become multi-designer efforts. As a result, architects of designs must determine how to divide the project, among multiple designers, to facilitate an efficient design process. The traditional approach to minimize complexity is to divide a design by blocks in a hierarchical and vertical manner. Challenges for the architect include how to divide functionality between blocks to accomplish two tasks, minimize interconnect between blocks and allow for use of existing intellectual property blocks.

Dividing the design by blocks provides several advantages to the design process. First, by pushing design blocks to lower level blocks, each level of hierarchy may become less complex. Larger schematics and Hardware Description Language (HDL)

007933-06101
15

representations are more prone to development errors. These development errors are, due to the size of the schematic or HDL description, harder to detect. Resultantly, a reduction in complexity makes it easier for the design team to develop and debug the schematics or HDL descriptions. Second, by dividing the design hierarchically, it enables the division of the design work among design teams. Third, proper division of design facilitates management of interconnect complexity.

However there are problems with using hierarchy to manage designs. First, hierarchy does not necessarily solve all of the problems mentioned above. For example, while introducing levels of hierarchy can make the HDL and schematic development less error prone, it still leaves the problem of the creation of HDL models or schematics for the hierarchy. Block level schematics and textual descriptions, except for trivially small ones can be too unwieldy to create. Second, the introduction of additional hierarchy has two undesired side effects. For example, there is increased simulation time due to the added interfaces. Additionally, additional hierarchy results in decreased synthesis and optimization efficiency due to complexities in optimizing across boundaries.

Even assuming that a design is properly divided hierarchically however, designs remain time consuming to enter. For example, schematic entry requires that the designer place each gate and provide interconnect information between components. This process is very time consuming. In a similar vain, entry of designs by having the user enter hardware description language models for a design require that the designer enter a textual description of components. Such a description still requires that a

designer manage the connectivity between components by matching outputs to inputs
in a text file.

09079638-061401
T01190"82964850

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 – Embodiment of an Interface Based Design table.

Figure 2 – Schematic diagram showing equivalent representation of the interface based design table of Figure 1.

Figure 3 – Embodiment of an interface based design table with multiple module instantiations.

Figure 4 - Schematic diagram that would be the equivalent of the interface based design table of Figure 3.

Figure 5A & 5B - VHDL model for embodiment of present invention shown in Figure 3.

Figure 6A & 6B - Flowchart showing method of creating HDL model from an embodiment of the present invention.

Figure 7A - Embodiment of an interface based design table showing arrays of modules and signals.

Figure 7B - Schematic diagram that would be the equivalent of the interface based design table of Figure 7A.

Figure 8 - Details for use of a signal in one embodiment of the present invention.

Figure 9 - Details for use of a signal vector in one embodiment of the present invention.

Figure 10 - Details for use of a signal array in one embodiment of the present invention.

Figure 11 - Details for use of a signal vector array in one embodiment of the present invention.

Figure 12 - Embodiment of the present invention showing signal attributes, module attributes and comments.

5 Figure 13A & 13B - VHDL module for the ICT embodiment shown in Figure 12.

Figure 14 - Interconnect Table for a first portion of a design.

Figure 15 - Interconnect Table for a second portion of a design.

Figure 16 - Interconnect Table for a complete representation of a design formed by merging the Interconnect Tables of Figures 14 and 15.

Figure 17 - Hardware to run an embodiment of the present invention.

Figure 18 - A block diagram of a software solution embodying the present invention as well as other design entry tools.

Figure 19 - Example of an Interconnect Table containing a bundle with expanded bundle components.

Figure 20 - The Interconnect Table of Figure 19 showing the effect of collapsing the expanded bundle.

DETAILED DESCRIPTION OF THE INVENTION

In the following description, various aspects of the present invention will be described. However, it will be apparent to those skilled in the art that the present invention may be practiced with only some or all aspects of the present invention. For purposes of explanation, specific numbers, materials and configurations are set forth in order to provide a thorough understanding of the present invention. However, it will also be apparent to one skilled in the art that the present invention may be practiced without the specific details. In other instances, well-known features are omitted or simplified in order not to obscure the present invention.

Parts of the description will be presented in terms of operations performed by a processor based device, using terms such as data, tables, requesting, determining, retrieving, displaying, and the like, consistent with the manner commonly employed by those skilled in the art to convey the substance of their work to others skilled in the art. As well understood by those skilled in the art, the quantities take the form of electrical, magnetic, or optical signals capable of being stored, transferred, combined, and otherwise manipulated through mechanical and electrical components of the processor based device; and the term processor include microprocessors, micro-controllers, digital signal processors, and the like, that are standalone, adjunct or embedded.

Various operations will be described as multiple discrete steps, in a manner that is most helpful in understanding the present invention, however, the order of description should not be construed as to imply that these operations are necessarily order dependent. In particular, these operations need not be performed in the order of

presentation. Further, the description repeatedly uses the phrase “in one embodiment”, which ordinarily does not refer to the same embodiment, although it may. Finally, “a portion of an electronic design” may refer, in addition to only a subsection of an electronic design, to a complete representation of the electronic design.

5 **Abbreviations**

This section contains the definitions for abbreviations that are used throughout this document. Some are well know to those skilled in the art. Others are defined within this patent application.

ASIC - Application Specific Integrated Circuit

FPGA - Field Programmable Gate Array

HDL - Hardware Description Language

ICT - Interconnect Table

IC - Integrated Circuit

IBD - Interface Based Design

15 **Overview**

What is desired is a way of solving the problems associated with hierarchy management and time consuming design entry. The present invention advantageously facilitates the rapid entry of complex design using a compact format, while at the same time reducing the issues associated with improper or non-optimal interface descriptions.

20 Additionally the present invention facilitates provision of clear and concise

instantiations of external intellectual property components, blocks or any other object that is a constituent element of an electronic design.

In this embodiment of the present invention, the second column **110**, after the column of signal names, is a special column called the interface column that defines the design and the interface for that design. The interface is defined by sigName1 **140** and sigName2 **180**. sigName1 **140** is the sole input to this view and sigName2 **180** is the sole output. Figure 2 shows a corresponding block diagram for the table that is shown in Figure 1.

In this embodiment of the present invention, the signal names are shown in the rows of the table and the instances are shown in the column. However, signals can be shown in columns and instances can be shown in rows. At the intersection of a row and a column is a cell that is termed a synapse. An empty synapse indicates that there is no connectivity between the signal corresponding to the intersecting row and the instance associated with the intersecting column.

In the present embodiment, a header column contains the names of the signals that exist for the current level of hierarchy. As can be seen for this embodiment, there are 4 signals: sigName1, sigName2, sigA and sigB. Similarly, this embodiment contains a header row containing, among other things, information for instances that appear in the current level of hierarchy.

In the present embodiment, the input and outputs can be seen by the interface column **110** of the table. As indicated at the intersection of the interface column **110** and the row corresponding to signal *SigName1* **140**, by the inclusion of the "I" in the

or and "O", the entries for U1 have the names of the corresponding formal port names for the module *Module2*. In addition, we see that U0 drives the sole output to the current block, SigName2 180.

Figure 3 shows another embodiment of the present invention. The schematic diagram, which would result from the table of Figure 3, is shown in Figure 4. This embodiment shows an implementation containing multiple instantiations of a component. *Module2* 310 is instantiated twice as shown in Figure 4. The instances of *Module2* are U1 320 and U2 330.

Design Description Output

As discussed below, there may be computer implementations of the present invention. To facilitate subsequent usage by downstream tools of a design description created using the present invention on these computer systems, it is desirable to have the ability to output the description of a design. In one embodiment of the present invention, the tabular format can be written out into a HDL representation. For an example, refer again to Figure 3. Recall that Figure 3 shows an ICT representation of a design. Figures 5A and 5B show a corresponding description in the hardware description language VHDL for this table.

Figures 6A and 6B show a flow chart for one embodiment of writing the VHDL model of Figures 5A and 5B from the table of Figure 3. The first step 610 in the writing of the VHDL model is the determination of which packages are in use and consequently which library and use clauses 620 are required. In this example, this determination is made based on the signal types in use. Determination of signal types will be discussed

0879838-06101
10130-828280

below. Lines **503** and **504** show declarations for the IEEE library containing the definitions for the `std_logic` signal type used in this example. Next **630**, lines **506-510** show the VHDL entity statement that is written out, based on the name of the interface and its ports, as described in the interface column **340**. The interface name from the column translates to the entity name **506**. The ports on the entity are derived from the synapses containing the appropriate indication (in this embodiment “I” for inputs and “O” for outputs) in the interface column. From this we see that Signal1 **507** is the sole input to the entity Top and Signal2 **508** and Signal3 **509** are the outputs. Next, the body outline **512, 532, 554** for the architecture are written **640**. After the body outline for the architecture is written, the signal declarations for the body need to be determined **650**. These signals are simply the signals that appear in the table that are not already declared in the entity declaration. Such signals are to be written in the declarative portion of the architecture body. In this example, these signals are the two constituent signals for bundle Bundle1, namely *sigA* **514** and *sigB* **515**. In the declarative section, after the signal declarations are written, the component declarations are to be written. In this embodiment, these are indicated by the columns of the table to the right of the interface column. While there are three columns in this example, there are only two components shown in Figure 3. The three columns contain instances U0, U1, U2 and components Module1 **350** and module2 **310**. After determining whether there are instances still to be processed **660**, we begin by processing the first column to the right of the interface column **670**. In this case we ask if the component associated with this instance has already been written. In the case with U0, the answer is no and the

5
10
15
20

statement section of the architecture. In this embodiment, we see there is a component instantiation statement for each instance in the table; U0 **534-539**, U1 **541-545** and U2 **546-550**. The interconnect for the instantiations are directly translated from the table. In the embodiment shown in Figure 5, the instantiations employ named association. For example, in the case of the U1 instantiation of Module2, the "in1" port is connected to the "sigA" signal in Top **542**. This connection is indicated by the appearance of the "in1" in the synapse intersecting *sigA* row and the *U0* column **360**. Finally, after the component instantiations are written to the statement section of the architecture, lines 551 and 552 show the breaking out of the individual signals *sigA* and *sigB* from the bundle *Bundle1*.

For use with VHDL, a signal type must be provided to enable the tool to write the description. In this embodiment, a default value is provided and is of type "std_logic". In one embodiment of the present invention, a default value of "bit" is used. In another embodiment, the default value will not be assumed and the user will specify type information in an additional column. In yet another embodiment the default value will not be assumed and the user will be prompted for a type to use for signals when the request to write the VHDL is made.

Other methods to output design descriptions to downstream tools can be used. For example, in one embodiment of the present invention, the design would be written out in Verilog HDL. In another embodiment of the present invention, the design is written out in a proprietary database format.

Additional Table Features

Signal and Module Arrays and Signal Vectors

To aid in the compaction of data, one embodiment of the present invention supports the use of arrays to describe signals and modules in a design. Figure 7A shows one embodiment where signal and module arrays are used. In this example, a design whose name is *controller* is shown. In this embodiment, the last column shown is the interface column **702**. From this column, we see that *controller* has two inputs; inSig1 and inSig2. In addition, *controller* has an output, *outSig*, which is actually two signals, *outSigA* and *outSigB*. Figure 7B shows the corresponding schematic representation of the interface based design description of Figure 7A.

In this embodiment of the invention, braces are used to indicate an array of names for modules or signals. This method can be used to create a second dimension to modules and a second dimension to signal vectors. For example, referring to Figure 7A, the definition for the array of "F" modules can be shown in a column header **705**. As shown here, the syntax of $F\{A:B\}$ can be used as a shorthand for generating two modules FA **710** and FB **715** as shown in Figure 7B. This array naming convention can work for alphanumeric and is a simple way to replicate slices for designs that have repeating structures.

The embodiment of the present invention shown in Figure 7A also demonstrates the ability to have vectors for signals. Signal *run* is a bus that is two bits wide as denoted by the range indicator "6:5" **725**. The *run* bus is driven by the module "state_machine" **720**. In this embodiment, the positional notation of the 6:5 for the run

embodiments can use this as simply a comment field for the table and not write out the comment when writing an HDL file or write out the comment in block comment format if the HDL supports block comments.

Figures 13A and 13B show an HDL listing of an output from the table of Figure 12. The port declaration statement in the entity declaration, at lines **1310** and **1320**, shows the output of the comments from the table of Figure 12. The entity declaration also shows the signal attributes for the input and output ports to the interface at lines **1330** and **1340**. The declarative part of the architecture, for the HDL written from the table of Figure 12, shows the attribute statements at lines **1350** and **1360** for the internal signals shown in the table.

For embodiments to support the ability to have non-instance columns, there needs to be some way of indicating that the column does not correspond to an instance. In embodiment shown in Figure 12, there is a hidden column type field tied to each column. This field provides information about whether a column is describing an instance of a module, a comment or a signal attribute.

Instance Attributes

In a manner analogous to the signal attributes, an embodiment of the present invention may support instance attributes. As shown in Figure 12 and the corresponding HDL in Figures 13A & 13B, there is an instance attribute called **cellName**. As shown on line **1370**, the value of this attribute for the U0 instance of Module1 is "Rev3". Note that, in this embodiment, the behavior of the instance attributes is slightly different from the signal attributes. If there is no entry in the field for

the instance attribute, the attribute is not written out. So, as shown in Figure 12, there is no entry for cellName for Module 2, resultantly there is no attribute written to the file.

Attribute Output Options

As discussed above, in one embodiment of the invention, attribute information can be output in an HDL description of the design represented by the table. For example, a user enters attribute information that relates to a subsequent synthesis process in the columns of a table. The user may then write an internal script which will be used by an HDL generator to create in-line HDL/embedded constraints and insert them in the generated HDL file.

In one embodiment of the invention, the attribute information is output in a tab separated value (TSV) format. A user can write an external script that will access the TSV format file containing the attribute/property values and create a stand-alone constraint file that another design or verification tool may read automatically.

In yet another embodiment, the invention will generate a synthesis constraint file directly without the need for a users script. The constraint file will be in the proper format for the targeted synthesis tool that the user specifies and is to subsequently process the HDL design description file.

Multiple Table Manipulation

Table Merging

As mentioned, one of the advantages of the present invention is the ability to have multiple designers or teams work on different portions of a design while also

facilitating easy combination of efforts into a single design representation. This can be accomplished by designing with different tables and then merging the tables together.

Figure 16 shows the result of one embodiment of the present invention that merges the tables in Figures 14 and 15. Figure 14 shows a portion of a design called *example* containing three blocks; two *function_one* blocks and a *control* block. Figure 15 shows another portion of the same design containing two blocks; *other_function* and *monitor*. In this embodiment of the invention, checking is performed on the two tables prior to merging. The checking looks for conflicts in data that have diverged. For example, each connection to an instance is checked to make sure that the direction, range and type match (or is handled by a type converter). Additionally, in this embodiment of the invention, signal attribute values must match exactly for the same signal in different tables. Other embodiments of the invention can establish any set of rules regarding the merging of data.

As with other tables generated by this invention, it may be desirable to have a table exported by an embodiment of the present invention. This exporting, as previously mentioned may be in the form of an HDL. In one embodiment of this invention involving the generation of a Verilog hardware description model; multiple outputs, no outputs or no inputs are reported upon merging of tables. This information is kept and is flagged during generation of the HDL model from the merged table. This ensures that the information is communicated to the user at the time that the tool writes a model that can be used by other tools.

Table Extraction

A component table of a design description can be created. In one embodiment of the present invention, rows of signals are selected by a user. Based on these rows of signals, the modules that drive, or are driven by, the signals in the selected row are also selected. The user selected rows of signals and the corresponding selected modules are extracted from the table and used to create a component table of the original description.

User Device Embodiment

Hardware

Figure 17 illustrates one embodiment of a user apparatus suitable to be programmed with the utility application of the present invention. As shown, for the illustrated embodiment, user device **1700** includes processor **1702**, processor bus **1706**, high performance I/O bus **1710** and standard I/O bus **1720**. Processor bus **1706** and high performance I/O bus **1710** are bridged by host bridge **1708**, whereas I/O buses **1710** and **1720** are bridged by I/O bus bridge **1712**. Coupled to processor bus **1706** is cache **1704**. Coupled to high performance I/O bus **1710** are system memory **1714** and video memory **1716**, against which video display **1718** is coupled. Coupled to standard I/O bus **1720** are disk drive **1722**, keyboard **1724** and pointing device **1728**, and communication interface **1726**.

These elements perform their conventional functions known in the art. In particular, disk drive **1722** and system memory **1714** are used to store permanent and working copies of the mechanical design system. The permanent copy may be pre-

loaded into disk drive **1722** in factory, loaded from distribution medium **1732**, or down loaded from a remote distribution source (not shown). Distribution medium **1732** may be a tape, a CD, a DVD or other storage medium of the like. The constitutions of these elements are known. Any one of a number of implementations of these elements known in the art may be used to form computer system **1700**.

Certain embodiments may include additional components, may not require all of the above components, or may combine one or more components. Those skilled in the art will be familiar with a variety of alternative implementations.

Software User Interface

As embodied in a computer system, the present invention can be a stand-alone application or as part of a suite of design entry applications. Figure 18 shows an embodiment of the present design in a suite of design entry applications. The ICT editor **1810** is shown together with a block diagram editor **1820**, a text editor for direct entry of HDL files **1830**, and a state machine editor **1840**. In this embodiment, all the design entry applications have a common portion to the user interface **1850**. In addition, there is a common "back-end" that allows the user to combine different designs and have them written out in a hardware description language format. **1860**. As mentioned in previous discussions, the entry of information in the present invention can be in a manner that is HDL independent.

One feature of using a software interface with the present invention is the ability to collapse and expand signal bundles and buses, and signal and instance arrays. Figure 19 shows a portion of a table from the one embodiment of the present invention.

In this embodiment there exists a bundle, *mybundle* 1910, which contains two signals *data[32]* 1920 and *R/W* 1930. In this embodiment, it will be possible to collapse bundles to simplify the table. For example, in Figure 19, by double clicking on the bundle 1910, *mybundle*, the bundle is collapsed as shown in Figure 20. In such a case, a complex connection is created. This complex connection is shown by an "*" in the table. In this computer embodiment of the present invention, the user can perform the same operation on buses and arrays of instances and signals.

In one embodiment of the present invention, the software user interface will support the ability for the user to view a block diagram from the table description. As an example, refer back to Figures 3 and 4. Figure 4 would be an example of a block diagram that would be generated from the table of Figure 3. In one embodiment of the present invention, the user can select the table and choose an option from a pull down menu to "Generate Block Diagram ...". Pull down menus are well known in the art and will not be described further. It is desirable to have the ability to view a block diagram of a table since many designers are familiar with the representation of a design in block diagram format. This enables the user to rapidly compare the table representation with that which the user is familiar - block diagrams.

In one embodiment of the present invention, the use of signal and instance attributes can be facilitated using pop-up menus in the user interface. Popup menus are known in the art and the details for implementation will not be provided. Recall from the previous discussion that embodiments of the present invention use instance and signal attributes. In this embodiment, information about VHDL packages that are to be

used in the design process are provided to the interface based design tool. This can be accomplished by querying the user at setup time for the design package information.

Once the design package information has been provided, the package information can be scanned to determine what types are defined for signals and instances. From this

5 information, the current embodiment of the present invention can build a list of the available attributes for signals and instances. This list can be presented to the user, for example, via a pop-up menu when the user has a pointing device over the table.

Conclusion

Thus, it can be seen from the above descriptions, a novel method of providing a compact description of the interconnect for a given level of hierarchy of a design is provided. Such descriptions enable a more rapid entry of complex designs using a compact format for representation of such designs.